:hager



(GB) Changeover switch — User instructions

(FR) Commutateur modulaire — Notice d'instructions

6H 5119.b

HIM302 / 304 / 306 / 308
HIM402 / 404 / 406 / 408

20 A - 80 A

	Ref. Switch Réf. Commutateur	Rating Calibre	AC	Ref. Terminal shrouds Réf. Capot cache-bornes
❶	HIM302	3 x 20 A	AC-23 A	HZC211
	HIM402	4 x 20 A		HZC212
	HIM304	3 x 40 A		HZC211
	HIM404	4 x 40 A		HZC212
❷	HIM306	3 x 63 A	AC-23 A	HZC213
	HIM406	4 x 63 A		HZC214
	HIM308	3 x 80 A		HZC213
	HIM408	4 x 80 A		HZC214



(A) Direct operation / Commande directe

(B) Front operation / Commande frontale



Configuration

Edition 10/09 IS 535619-B / RECTO-VERSO / S blanc offset quadri 80g/m²

⚠ HAZARDOUS VOLTAGE

This equipment must be installed and serviced only by qualified electrical personnel. Turn off all power supplying this equipment before working on or inside equipment. Always use a properly rated voltage sensing device to confirm power is off. Replace all devices, doors, and covers before turning on power tothis equipment.
Failure to follow these instructions will result in death or serious injury.

⚠ TENSION DANGEREUSE

L'installation et l'entretien de cet appareil ne doivent être effectués que par du personnel qualifié. Coupez l'alimentation de cet appareil avant d'y travailler. Utilisez toujours un dispositif de détection de tension à valeur nominale approprié pour confirmer que toute alimentation est coupée. Replacez tous les dispositifs, les portes et les couvercles avant de mettre cet appareil sous tension.
Si ces précautions ne sont pas respectées, cela entraînera la mort ou des blessures graves.





Use 75°C Cu wire only / Utiliser uniquement du fil cuivre 75°C		
	❶ ❷ 9 mm - 12 mm	
	1,5 mm² - 16 mm²	❶ 3 Nm
	2,5 mm² - 35 mm²	❷ 3,5 Nm





* Possible assembly with two screws
Montage avec 2 vis possible

L = X + 30 mm







Total width = A1 + (x) x A2

REF	(x) max
HIM302	4
HIM304	
HIM306	
HIM308	
HIM402	2
HIM404	
HIM406	
HIM408	

	A mm	A1 mm	A2 mm	B mm	AD mm	B1 mm	C mm	H mm	H1 mm	N mm	M mm	T mm	T1 mm	T2 mm	T3 mm
HIM302/304	140	97,5	8,8	147	48,5	68	110	84	93,5	75	52,5	15	11,25	37,5	30
HIM402/404	140	127,5		147		68				75		15	11,25	37,5	30
HIM306/308	170	105		199		76				85		17,5	8,75	42,5	35
HIM406/408	170	140		199		76				85		17,5	8,75	42,5	35

Hager 10.2009